

PATENT APPLICATION of

Sanjay Agarwal

for

TITLE:

NETWORK TRAFFIC BASED ADAPTIVE POWER MANAGEMENT SYSTEM FOR COMPUTER NETWORKS

CROSS-REFERENCE TO RELATED APPLICATIONS:

This application is entitled to the benefit of Provisional Patent Application Ser. 60/248,951, filed 2000, November 14.

STATEMENT REGARDING FEDERALLY SPONSORED RESEARCH AND DEVELOPMENT:

Not Applicable.

SEQUENCE LISTING:

Not applicable.

REFERENCE TO A MICROFICHE APPENDIX:

Not Applicable.

BACKGROUND OF THE INVENTION:

The present invention relates generally to power management of computer networks equipment, and more particularly, for optimizing power management based on traffic through the network as applied to the cooling and ventilation system of the equipment. The present invention is related to U.S. patent classification definitions 713/323, and 713/324.

Computer networking equipments form the backbone for transfer of electronic information over variety of transfer medium that includes copper cable, optical fiber, and air for wireless data transfer. Before traveling over the transfer medium, the information is processed in the electronic form in the integrated circuits. The current rate or speed of information transfer is in the range of 10 megabits per second, 100 megabits per second, 1000 megabits per second, and 10 gigabits per second (megabit = 1000,000 bits, gigabit = 1,000,000,000 bits), and increasing. The speed requirements are increasing and so are the switching requirements of the integrated circuits that drive the data. Higher traffic in the computer networks results in higher switching capacity, which results in higher amount of power consumption by the integrated circuits. The power consumed by the integrated circuit is directly proportional to the frequency of switching (described, for example in Neil Weste and Kamran Eshraghian, Principles of CMOS VLSI Design – A Systems Perspective, Addison-Wesley Publishing Company, 1988, at pages147-149, which is hereby incorporated by reference). Higher amounts of data correspond to higher amounts of switching activity within the integrated circuits. In effect, the power consumed by the integrated circuits is directly proportional to the amount of data that travels through the network. Electrical power consumed by the electronic components is in proportion to the heat generation of each of the components. Hence, the heat generation is directly proportional to the switching activity within the integrated circuit. The networking equipment is designed with ventilation and cooling system that removes the generated heat. A significant amount of power in the computer networking equipment is consumed by the ventilating system that keeps the integrated circuits cooled and in working condition. The optimal amount of cooling should be directly proportional to the amount of heat generated by the integrated circuits or the switching requirements of the integrated circuits.

Computer networking equipment continues to be the most extensive energy consumers placing considerable strain on the existing power supply systems. This strain on power supply systems extends from power used by individual companies to the power generation system of the utilities. The article in San Jose Mercury News dated January 7, 2000 titled "California Energy Crisis – State targets power suppliers for refunds" discusses the strain on electrical utility systems in the state of California. On page 20A of the news article, the article indicates that a Silicon Valley "server farm" – a building that houses hundreds of internet computers – can consume more than 200 megawatts of power a day. The article further indicates that 200 megawatts is more than 100 times the power consumption of a typical high-rise office building. Energy conservation to any extent in the computer networking equipment can help the utility system.

Inventors have created several system designs and solutions to achieve optimal power management in computer systems. Some of the methods and apparatus are as follows:

The computer equipment industry has a variety of schemes for controlling electrical power. U.S. patent 4,312,035 (1982) assigned to Richard E. Greene is an invention on apparatus for controlling electrical power in a data processing system. The patent describes a central control, monitor, and metering of application of voltage and time to each separate unit. This invention also includes a circuit for sequentially connecting the

voltage signals to the peripherals. The invention describes how a central system can be configured to selectively control power application to independent power consuming peripheral units. The block diagram for this invention is described in FIG. 1. This invention ignores activity within the integrated circuit components as the basis for conserving power. This invention does not indicate any power saving method for controlling the power usage in cooling and ventilation system.

Power management can also be achieved by monitoring inactivity of input/output devices. U.S. patent 6,128,745 (2000) assigned to Eric Christopher Anderson, and Henri Hayim Farhi describes power management inactivity monitoring using software threads. The patent describes assignment of individual timers to each input/output devices and then software monitoring of timers for time-out. In the event of time-out, the specific input/output device driver is sent a power reduction instruction. This invention configures devices to be in either power-save or active-mode based on timer elapsing. The flow chart diagram for this invention is as shown in FIG. 2. This invention does not discuss power management in the context of switching activity of integrated circuit components. This invention does not indicate any power saving method for controlling the power usage in cooling and ventilation system.

In U.S. patent 6,105,142 (2000) assigned to Lonnie C. Goff et al., we have a description on intelligent power management interface for computer system hardware. The patent describes power management in the context of Advanced Configuration and Power Interface (ACPI). The invention describes introduction of a power management processor. The objective of introduction of power management processor in this invention is to let the operating system perform routine power management functions. The power management processor implements sophisticated power management functions. The power savings is achieved by letting individual devices go into sleep-mode or active-mode depending on the activity status at any given time. The architectural diagram for this invention is as shown in FIG. 3. This invention discusses the introduction of power management processor in the ACPI environment.

Power management and heat dissipation inside the system has always been a concern to system designers. U.S. patent 6,101,610 (2000) assigned to William Eldred Beebe, and John Daniel Upton describe a computer system having thermal sensing with dual voltage sources for sensor stabilization. The computer system described employs a thermal sensor in the main CPU housing to detect operating temperatures. The computer system is then designed to get into an orderly shut down mode if the sensors detect that a pre-defined operating temperature has been crossed in the computer system. This invention uses a thermal sensor for detecting the trip point based on high temperatures in the CPU housing. Thermal sensors are expensive and require costly analog circuitry for precise detection system. The electrical diagram for this invention is described in FIG. 4. This invention uses thermal sensors as a means to determine condition of the components inside the equipment. This invention does not indicate any power saving method for controlling the power usage in cooling and ventilation system.

Power management can also be achieved by detecting on-hook and off-hook status for the computer system integrated with telephone systems. U.S. patent 5,958,055 (1999) assigned to David R. Evoy et al, describes this invention. The invention describes power management unit to detect on-hook or off-hook status of telephone to put the computer into either normal power mode or power saving mode. The block diagram for this invention is as shown in FIG. 5. This invention does not take into consideration the level of traffic or usage of the components that make the system equipment.

Power management is also an issue in portable computing systems. U.S. patent 5,954,820 (1999) assigned to Steven Robert Hetzler describes portable computer with adaptive demand-driven power management. This invention describes the method for managing power in a portable computer using past history of the various electrically powered computer components and a prediction of future user demands to determine power-save mode entry and exit conditions. The block diagram for this invention depicting power source and various energy-consuming components is as shown in FIG. 6. This invention utilizes historical data and a prediction of usage data to put individual components in power-save or exit-mode.

The invention described in U.S. patent 5,913,067 (1999) assigned to Dean A. Klein describes a system to manage power in the computer system based on activity at a particular IO device, and managing the idle timers associated with expiration times for each device. Upon expiration of the associated device idle timer, the system puts the I/O device in powered-down state. In this invention the power management is accomplished by switching devices on and off to optimize power. This invention as an apparatus for adaptive power management is described in FIG. 7. This invention uses timer-based system to put devices in power down modes based on the activity in the IO device.

The power management system design focus is monitoring the in-activity of different peripheral and input output devices and selectively putting the components in sleep mode. The current industry standard for system design in computer networking boxes is to provide a fixed constant amount of cooling and ventilation, which requires a constant operation of the fan system. This cooling and ventilation is used for removal of heat from inside of the networking equipment. This also results in constant noise generation in the proximity of the networking equipment.

Accordingly, the prior art power management systems ignore power savings that can be obtained based on using network traffic intensity data for controlling the cooling and ventilation systems in computer networking equipment. The power management systems of prior art also ignore the reduction in noise levels that can be achieved in computing environments if we can adaptively control the cooling systems based on network traffic levels.

## BRIEF SUMMARY OF THE INVENTION:

The present invention monitors the amount of data flowing through the system and adaptively controls the cooling and ventilation requirements based on the amount of network traffic. Control of cooling and ventilation systems power provides energy conservation for the complete system. The cooling and ventilation systems in the computer networking equipment are designed around mechanical fans. These fans supply the needed cooling air to keep the individual electronic components in working condition. At the same time, these fans are powered from the system power supply unit. The cooling fans themselves contribute to the power usage inside the networking equipment. This invention describes controlling the cooling requirements based on levels of network traffic to optimize the power consumed by the cooling fans. The invention also describes a cost-effective all digital system to achieve power management in cooling system design. The invention described here monitors the quantity of data traffic over the computer networks and uses the principles of pulse width modulation (PWM). The system then applies adaptive cooling and ventilation management in the computer networking equipment to achieve optimal power consumed by the networking equipment. The objective of the invention is to achieve energy conservation in networking equipment using cost-effective means.

## BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWING:

The features believed to be characteristic of this invention are set forth in the appended claims. The invention itself however, as well as further objects and advantages thereof, will best be understood by reference to the following detailed description of an illustrative embodiment, when read in conjunction with the accompanying drawings, wherein:

FIG. 1 is prior art and is a block diagram of a data processing system.

FIG. 2 is prior art and is a flow chart diagram of a timer-based power management system.

FIG. 3 is prior art and is an architectural diagram illustrating the relationship of the software and hardware components.

FIG. 4 is prior art and is an electrical diagram in block form of a computer system.

FIG. 5 is prior art and is a block diagram of a computer system with telephone system.

FIG. 6 is prior art and is a block diagram of the computer system illustrating the power source and the various energy-consuming components.

FIG. 7 is prior art and is a block diagram of a computer system with adaptive power management.

FIG. 8 is a block diagram of System description for power management in accordance with the present invention; and

FIG. 9 is a representation of Pulse Width Modulation (PWM) Link Signals in accordance with the present invention; and

FIG. 10 is the structure for Communications Link Interface used in the system described in FIG. 8 in accordance with the present invention; and

FIG. 11 is the plot of Internet traffic Index in accordance with the present invention.

#### REFERENCE NUMERALS IN DRAWINGS:

102 computer networking equipment	104 power management processor
106 cooling fan 1	108 cooling fan 2
110 cooling fan 3	112 cooling fan 4
114 power management processor	116 PWM (pulse width modulation) link
118 cooling fan A	120 options A, B, C, D
122 networking equipment	124 register m
126 register k	128 power management processor
130 communications link	132 global traffic index

#### DETAILED DESCRIPTION OF THE INVENTION:

The accompanying drawings, which are incorporated into and form a part of the specification, illustrate several embodiments of the present invention and, together with the description, serve to explain the principles of the invention. The drawings are only for the purpose of illustrating a preferred embodiment of the invention and are not to be construed as limiting the invention. In the drawings:

Figure 8 is System description for power management system. The figure illustrates a configuration for a power management system with computer networking equipment **102**. A power management processor **104** controls the speed and operation of the cooling ventilation fan systems **106 108 110 112**. A given network router can have ventilation fans located at different places based on the placement of the integrated circuits. Preferably, the ventilation fans are situated close to the heat generating devices. The figure illustrates 4 cooling fans but the systems can have higher or fewer cooling fans depending on the cooling requirements.

Figure 9 is Pulse Width Modulation (PWM) Link. The figure illustrates the control mechanism for the control of cooling fan A. Different pulse width modulated waveforms can be generated using power management processor **114**. Pulse width **116** of the applied waveform results in the drive states of the cooling fans **118**. The width of the pulse applied in any given time slot is a function of the power consumed by the cooling and ventilation system. Different options **120** of waveforms can be applied to the voltage terminals of the cooling fan in any given time slot  $\text{Time} = t$ . The power consumed by any electronic device is a product of applied voltage and current in the device over the time period  $t$ . The shaded area in the graph of pulse waveforms **116** for different waveform options is illustrating the power consumed in the device for different options **120**. Different options illustrated are Option A, Option B, Option C, and Option D. Depending on observed traffic, different options can be applied to keep the fan in drive condition. Option A can be selected for the lowest amount of traffic and Option D can be selected for the highest amount of traffic. Option B and Option C can be used for other intermediate intensities of traffic. The system is not limited to four options only. For any given option the fan will encounter a variation in drive state. The time duration for which it is driven or not driven is controlled by the PWM signal. Controlling the duty cycle of the applied power will result in power

savings. Duty cycle is defined as the ratio of the duration for which the fan is in on-drive state and the duration for which the fan is in off-drive state. The power management processor **114** has special hardware, which allows changing duty cycles quickly and applying the changed signal very rapidly to adapt to the changed environment of traffic intensity. This PWM signal is thus a function of the quantification of data traffic through the equipment. The system design can be made dependent on the resolution of optimal power control desired by the system designer.

The illustration in Figure 9 can also be explained by using variable voltage fan system for design of ventilation systems. The pulse width modulated waveform can be used to generate a variable voltage, which directly regulates the speed of the ventilating fan. In this case the speed of the fan can be made variable to the applied voltage that is sourced over the PWM Link **116**. This will be equivalent to applying the average voltage in different options to the cooling fan. As per the illustration of Figure 9, the average voltage over the time period  $t$  will be the highest in Option D and lowest in Option A. For example, average voltage in Option B will be  $V/2$ , in Option D will be  $V$ , in Option C will be between  $V/2$  and  $V$ , and will be less than  $V/2$  in option A. Different voltage levels can be configured with fine resolutions to achieve precise power regulations. The system designer can design the resolution and precision as per the requirements of the system equipment.

Figure 10 is Communications link interface. The idea of this system design is to off-load the network processor from doing any power management function with respect to the ventilation system in the equipment. The power management processor is equipped specifically with pulse width modulation capability, which allows it to efficiently control the ventilation system. The communication between the network processor and the power management processor will be through a communication link. Whenever, the network processor **122** experiences change in traffic intensity, it can communicate the change to the power management processor **128** by updating the internal registers (register  $m$  **124** and register  $k$  **126** in the figure) and communicated over the communication link. Alternatively, the power management processor can check the data traffic intensity at periodic intervals. The power management processor will control the cooling and ventilation system to provide optimal ventilation depending on the data communicated in the registers. Energy conservation is achieved by optimal drive of the cooling and ventilation system in the computer communication equipment.

The data traffic that flows in the networking equipment is processed before being delivered to the destination. The computer networking equipment processors keep track of the intensity of traffic in any given time interval. The traffic intensity value is stored in the  $m$  register. The traffic intensity data in  $m$  register is communicated to power management processor as the control data. The traffic intensity can be quantified into  $m$  bit register as indicated in Figure 10. The value of  $m$  can range from 8-bit to 16-bit or higher number of bits depending on the desired resolution of control. For example, an 8-bit representation would mean values from 00000000 to 11111111, which correspond to 0 to 255 in decimal representation. This 8-bit value can be

transferred to power management processor on periodic basis or the networking equipment can generate an exception and request communication whenever it experiences sudden changes in traffic intensity levels. The values in the m register reside as values of k register in the power management processor assuming value of m is equal to value of k. The contents of m register in networking processor/equipment are communicated to power management processor over the communication link.

The power management processor interprets the data in the k register. The interpretation of values in k register is programmed in software that runs on the power management processor. Different variations of pulse widths are configured depending on the contents of k register. For example, assuming higher values in k register correspond to higher traffic intensity, then value of 11111111 in k register (for k=8) can correspond to option D of the PWM signals of Figure 9. Similarly, the lowest value in k register of 00000000 can correspond to option A of Figure 9. The intermediate values can be configured for option B or C. Multiple options can be programmed depending on the traffic intensity. 8-bit representation of k and m registers result in as many as 256 combinations.

An additional option for the m and k register can also include the location of the cooling fan. The cooling system in the networking equipment is distributed. Sometimes, few data channels could be doing higher data traffic intensity with few channels without any data traffic. In this situation the ventilation cooling can be reduced to extremely low levels near channels with very low data intensity levels. For example, a system with 8 fans can have a 3-bit representation ranging from 000 to 111, which corresponds to 0 to 7 in decimal numbers. This could be the 3 most significant bits in the m and k registers followed by rest of the bits for PWM pulse width control. This 3-bit value can be used to globally shut off undesired ventilation fan. For example, a value of 101 (5 in decimal) in the 3 most significant bits in m and k register could indicate to the power management processor to keep the cooling fan 5 in off state all the time.

Figure 11 is the plot of Internet traffic index **132**. This graph shows a plot of data traffic over the Internet as a function of day and time. As evident from the graph, the traffic throughput goes through significant variations on any given day and time periods. The variations in usage pattern could also be dependent on the content that travels through the networking equipment. The content might be company specific intranet content or the content might be such that people access it globally. This invention seeks to use the traffic intensity patterns to design the system. The invention seeks to design energy efficient electronic equipment. The permission to use the data on Internet traffic report from Andover.net has been obtained.

The chart in figure 11 is a representation of global Internet traffic. Depending on the time zone for the equipment, the average networking equipment or system can experience almost a similar pattern of traffic density. This invention will use this information and process it to design adaptive control of ventilation and cooling system resulting in power savings.



This system described in Figure 8, Figure 9, Figure 10, and Figure 11 can be made part of the electronic equipment operating at high frequencies and which can handle very high quantities of data. This invention may be utilized without restriction as to the type of microprocessor used as power management processor. In particular, power management processor may be an 8-bit, 16-bit, 32 or 64-bit processor. The choice of processor is primarily dependent upon the amount of non-power management related functions that are to be supported by power management processor. Additional specialized circuitry can be added around the microprocessors to simplify generation of pulse width modulation waveforms.

The power management function and the power management processor can be integrated on the integrated circuit of computer networking equipment or the network processor. This can result in cost savings and integration of functionalities. The illustration in Figure 8 is a system description for implementing optimal power efficient networking equipment. The function can also be achieved by integrating the pulse width modulation capability within the networking equipment. The function of generating variable voltage to drive cooling fans at variable speeds can also be made a part of networking equipment.

Reduction in ventilation fan speeds and the reduction in times for which the fan is in drive state also result in lower noise emissions. Because of the nature of networking equipment and proximity of networking engineers in the vicinity, lower noise emissions is an important consideration. The concepts of power management described here are also applicable for networking equipment that has Storage Area Network (SAN) or wireless networking components.

Savings in energy is an important consideration in selection of electronic devices especially in countries where energy systems are running at maximum capacity levels or in places where electrical energy is in short supply. The growth of Internet is directly related to the rate at which Internet equipment can be deployed. In many applications of the equipment, the deployment is conditional on the energy requirements of the equipment.

The preceding examples can be repeated with similar success by substituting the generically or specifically described components and operating conditions of this invention for those used in the preceding examples. Although the invention has been described in detail with particular reference to these preferred embodiments, other embodiments can achieve the same results. Variations and modifications of the present invention will be obvious to those skilled in the art and it is intended to cover all such modifications and equivalents. The entire disclosures of all references, applications, patents, and publications cited above, are hereby incorporated by reference.

## CONCLUSION, RAMIFICATIONS, AND SCOPE OF INVENTION:

Accordingly, the reader will see that the system designed with energy conservation and power management in mind can use this invention to design systems that want to achieve energy conservation objective. The system uses network traffic intensity data levels coupled with pulse width management (PWM) technique to control cooling inside networking equipment. The function of power management processor can be implemented using a separate processor, which can perform micro-controller or digital signal processing (DSP) functions as well. The function of power management processor can be integrated on to the existing networking integrated circuits. Cooling fans contribute to significant noise levels when a series of networking equipment is deployed within a facility (like server-farm). Control of cooling systems will result in reduction in noise levels in the networking equipment facility. The invention can be applied to a heterogeneous system that could comprise of wired, storage, and wireless networking equipment.

11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000